

Panasonic TDA30 Phone System User Guide

by Project Telecoms - 0406 611 538 - www.projecttelecoms.com.au

To enter Programming Mode:*

From extension 101, press 'PROG' (displayed on screen of KX-T7630 handset or any model above) -> Press * # followed by password **1 2 3 4** -> the handset will now display 'Sys-Pgm No?'

To change the time and date: (in Programming Mode)*

Press **000** -> handset will display 'Date & Time Set' -> press **enter** -> change date settings, then press **AUTO DIAL/STORE** key on handset -> the key will light up red and tone will sound to confirm save -> press **down** arrow to scroll to time settings and change accordingly -> then press **AUTO DIAL/STORE** key on handset to save

To change extension names: (in Programming Mode)*

Press **004** -> handset will display 'Ext Number' -> press **enter** -> select extension number you wish to change -> enter name using keys on handset -> then press **AUTO DIAL/STORE** key on handset to save -> scroll down or up to change other names in the same manner

To program extension key:

Press 'PROG' -> press key you would like to program -> press **1** on number pad -> Enter desired extension number -> to save, press **AUTO DIAL/STORE**

To program speed dial key:

Press 'PROG' -> press key you would like to program -> press **2** on number pad -> Enter **0** (outside line) followed by phone number -> to save, **AUTO DIAL/STORE**

Incoming call pick up (first incoming call):

Go off hook, then dial ***4 0 0 1**, or to pick up from another specific ringing extension, dial *** 4 1** followed by their extension number -> call will connect

Group paging (all extensions):

Go off hook, then dial *** 3 3 0 1** -> begin announcement after tone

To forward extension (specific handset only):

Go off hook, then dial *** 7 1 0** followed by; **2** for **immediate fwd**, **5** for **busy/no answer fwd**; then enter destination e.g. 101 or 0 then phone number then press #

To transfer a call to another extension:

During a call, press 'TRANSFER' followed by the **extension number** you wish to transfer the call to -> wait for the extension to answer, then **announce the call** to them, or simply hang up and wait for them to answer it (the caller will be on hold until it is answered)

To make a conference call:

During the initial call, press 'CONF' -> select **another outside line**, then **dial a phone number** -> when call connects, press 'CONF' again to link the calls -> to add more parties, repeat this process

To place a call on hold:

While on a call, press 'HOLD' key -> the line key will appear **flashing green** on your handset and **flashing red** on any other handset

To call the last number dialled:

Go off hook, then press the 'REDIAL' key -> wait for call to connect

To check incoming/outgoing call log:

Press 'MENU' -> scroll down to **incoming call log** or **outgoing call log** -> press enter -> scroll list up or down to check the log
****incoming call log requires caller ID card installed and network availability****

To play background music (per handset):

Go off hook, then dial *** 7 5 1 1** for ON or *** 7 5 1 0** for OFF

To set do not disturb:

Go off hook and dial ***7 1 0 1** for ON or *** 7 1 0 0** for OFF -> set per extension



For further assistance, please call;

Project Telecoms on 0406 611 538

www.projecttelecoms.com.au